

DS137

Low Cost digital playback unit

Features:

- High Quality Stand alone playback unit, ideal for sound effect and short messages.
- Plays multiple sound, up to 31 different sounds consecutively.
- 1 minute of playtime at 16 Khz sampling rate (32 seconds at 32 Khz).
- Built in 8 watt amplifier.
- 4 digital input for direct connection to push buttons, sensors etc.

Applications:

- Sound effect for Haunted Houses, Mini Golf Courses, Shooting Galleries etc.
- Sound effect for small exhibits and Animation.
- Sound system for point of purchase displays, vending machines etc.

Specifications:

Playtime at 16 Khz1 minute Sampling rate 16 & 32 Khz
Voltage & Power12 Vdc, 1 Amp Audio Storage 1 Pc, 4 Meg Eprom
Inputs4 digital, 1 IR Audio filesADPCM
Outputs .1 Transistor NPN, 200mAmp Amplifier built in 8 watt
Audio Line out 0.8 V P/P Number of sound effects 31 Max
Enclosure size, S unit (plastic table top unit) 9" W X 7" L X 2" H