

# *SR4 – MP3 audio Solid State Audio Player*

## **Features:**

- Plays mp3 (xxx.mp3) audio files.
- Plays from Compact flash card.
- Built in 14 Watt stereo amplifier and Motion Detector port.
- 5 digital Input, binary connection to 31 push buttons and sensors.
- Inputs are programmable to play different audio files.
- Optional output board to trigger 4 relays in sync with audio/video. Max 16 relays.
- Compact unit size, only 6.5" W X 4.5" D X 1.2"H.



## **Applications:**

- Audio player for Museums and Science Center exhibits.
- Audio player for Interactive travelling exhibit.
- Audio information system for Theme Parks, Go-Kart tracks, Family Fun Parks.



## **Specifications:**

Voltage & Power ..... Switching 12 Vdc, 1 Amp  
 Audio storage... Compact Flash card, 4G max  
 Digital input, TTL Binary.. 5 Screw on terminal  
 Audio File format ..... MP3 and Wav  
 Bit rate ..MP3 @320kbps,Wav @16 bit 48 Khz  
 Audio amplifier ..... Stereo, 14 Watt  
 Video File format ..... Mpeg2 and VOB (DVD)  
 Std Video out ..... Composite and S Video out  
 Metal enclosure size ..... 6"W X 4.5" D X 1.1"H

AC input ..... 120 – 240VAC, 50-60Hz  
 Serial port ..... RS485,RJ12 connector 6 wire.  
 Volume control ..... Digital, 2 screw on terminal  
 Motion detector ..... RJ11, 4 wire  
 Audio Line Out, Stereo ..... RCA, 2 V p/p  
 Headphone Amplifier ..... Stereo, 100 mWatt  
 Video bit rate ..... Max 9 Mbps  
 PC Video out ..... VGA, DB15 at 640 X 480  
 Weight including P.S ..... Approximately 2.1 lbs

**Akman Inc**

[www.akman.com](http://www.akman.com)

Tel: (407) 948 0562 Fax (321) 459 1086